# How to (cont...):

#### **REDIAL A NUMBER**

To call the last dialled number:

Press twice when the phone is idle to dial the last dialled number.

To call a previously dialled number:

- 1. Press to enter the Placed Calls list.
- 2. Press ( ) or ( ) until you reach the desired entry in the list.
- 3. Press or the **Send** soft key to place the call.

#### MUTE OR UN-MUTE A CALL

Press to mute or un-mute an active call.

#### **FORWARD A CALL**

- Press the Menu soft key.
- 2. Select Features and then Call Forward.
- 3. Select the desired forward type: Always Forward, Busy Forward, or No Answer Forward.
- 4. Enter the destination number you wish to forward calls to.
- For **No Answer Forward**, press ( ) or ( ) to select the desired ring time.
- Press the Save soft key to accept the change.

#### CREATE A CONFERENCE CALL

- 1. Press the **Conf** soft key during an active call. This will place the call on hold.
- 2. Enter the extension or external number of the second party, then press the **Send** soft key.
- 3. Press the Conf soft key again when the second party has answered the call.
- All parties are now joined in the conference call.
- 4. Press the **End Call** soft key to disconnect all parties.

### PLACE A CALL ON HOLD & THEN RESUME THE CALL

To place a call on hold:

Press the **Hold** soft key during an active call.

To resume a call from hold:

Press **Resume** soft key when a call is on hold.

If there is more than 1 call on hold:

• Press • or • to select the desired held call, then press the **Resume** soft key to retrieve the desired call.




# Yealink SIP-T42G Ultra-elegant Gigabit IP Phone

# **Quick Reference User Guide**



# Layout & Features:



# How to:

## **PLACE A CALL**

#### Using a handset:

- 1. Pick up handset.
- 2. Enter number and press the **Send** soft key.

#### Using a headset:

- 1. With the headset connected, press 📵 to activate headset mode.
- Enter number and press the Send soft key.

#### Using speakerphone:

- 1. With the handset on-hook, press 📵
- 2. Enter number and press the **Send** soft key.



You can alternate between headset, speakerphone and handset by pressing the corresponding key.

# ANSWER/END A CALL

#### Using a handset:

Pick up handset / Return handset or press End Call soft key.

#### Using a headset:

Press (2).

## Using speakerphone:

• Press 🗐.

#### TRANSFER A CALL

Blind Transfer - The call is transferred directly without the need to announce the caller:

- 1. Press or the **Transfer** soft key during the active call, the call is then placed on hold.
- 2. Enter the receiving number you want the call transferred to and press #\*\*\*
- B. Press (G) or the **Transfer** soft key.

Attended Transfer - Allows you to announce the caller prior to releasing the call:

- 1. Press (c) or the **Transfer** soft key during the active call, the call is then placed on hold.
- 2. Enter the number you want to transfer to and press #......

When the second party answers, announce the call and then press (FC) or the **Transfer** soft key.

#### **ACCESS VOICEMAIL**

- 1. Press 🖾 or press the **Connect** soft key.
- For new messages, press 1
- For saved messages, press 2 ABC
- For advanced voicemail settings, press 5\_s

# MANAGE CALL HISTORY

- 1. Press the **History** soft key to view the **Placed, Missed** or **Missed** call log.
- 2. Press ( ) or ( ) to scroll through the list.
- Press the **Send** soft key to place a call.
- Press the **Delete** soft key to delete the highlighted entry from the list.
- Press the Option soft key and select Add to Contacts to add the entry to the local directory or select Add to Blacklist to add the entry to the blacklist.

# **ADD A NEW CONTACT**

- 1. Press the **Directory** soft key and then press the **Add** soft key.
- 2. Select the **Directory** the contact will be added to.
- 3. Enter the contact's **Name** and **Number.**
- 4. Press the **Save** soft key.